


This time-saving feature allows users to define Speed Dial options for specific numbers using short two (2) digit codes (00-99) prefixed by the # sign. Certain Speed Dial 2-digit code combinations will conflict with some Calling Feature Star Codes. These Star Codes are listed within the setting dialog to assist the user.

1. Sign into the Voice Services Portal website.
2. Go to Settings or Click on the [View All Features](#) link in the Basic Features widget on your Dashboard to view Settings.
3. Click on the View/Edit drop-down arrow adjacent to Speed Dial to begin.



Add a Speed Dial Contact

1. Click on **Add Contact**.
2. Enter **First Name** and **Last Name**.
3. Enter at least one (1) **Phone Number** (10 digits, no spaces or special characters) in the appropriate field (Home, Work, Mobile)
4. **Primary Phone**: Select the type from the drop-down menu (Home, Work, or Mobile)
5. Select from the available (unused) list of **Speed Dial Codes** using the drop-down menu (00-99). (Check Star Codes for conflicts)
6. Click the **Save** button to submit the new Speed Dial Code and close the *Edit* view.

Edit a Speed Dial Contact

1. Click **Edit** next to a Speed Dial Contact in the list.
2. Make changes to **name**, **numbers**, **primary assignment**, or **code**, as needed.
3. Click the **Save** button to submit the change and close the view.

Delete a Speed Dial Contact

1. Click within the checkbox in the first column to select an item in the list.
 2. Click on the **Delete** button below.
- OR**
1. Click the **Edit** link next to a Speed Dial Contact to open its Criteria dialog.
 2. Click the **Delete** button.
 3. Click the **Exit** icon to return to the *Edit* view.
 4. Click **Save** to submit the changes and return to **Settings**.

Export Speed Dial Contact List

Click on the **Export** button to automatically download a .csv format report containing the current list of Speed Dial contacts which can be saved to a local folder or printed, as desired.

Speed Dial Star Codes

- *74 = Speed Dial 8
- *75 = Speed Dial 100